
TUNG-SOL -

TRIODE PENTODE


MINIATURE TYPE



COATED UNIPOTENTIAL CATHODE

FOR USE AS A COMBINED OSCILLATOR AND MIXER IN TELEVISION RECEIVERS

ANY MOUNTING POSITION



BOTTOM VIEW BASING DIAGRAM JEDEC 9GF

GLASS BULB
MINIATURE BUTTON
9 PIN BASE E9-1
OUTLINE DRAWING
JEDEC 6-2

THE 5CG8 IS A MULTIUNIT TUBE OF THE 9 PIN MINIATURE CONSTRUCTION CONTAINING A MEDIUM-MU TRIODE AND SHARP CUTOFF PENTODE IN ONE ENVELOPE. IT IS DESIGNED PRIMARILY FOR USE AS A COMBINED OSCILLATOR AND MIXER IN 600 MA. SERIES HEATER OPERATED TELEVISION RECEIVERS UTILIZING AN INTERMEDIATE FREQUENCY IN THE ORDER OF 40 MC. THERMAL CHARACTERISTICS OF THE HEATER ARE CONTROLLED SUCH THAT HEATER VOLTAGE SURGES DURING THE WARM-UP CYCLE ARE MINIMIZED PROVIDED IT IS USED WITH OTHER TYPES WHICH ARE SIMILARLY CONTROLLED.

DIRECT INTERELECTRODE CAPACITANCES

	WITH SHIELD ^A	WITHOUT SHIELD	
PENTODE GRID 1 TO PENTODE PLATE: (PG1 TO PP) MAX.	0.02	0.04	ρf
PENTO DE INPUT: PG1 TO (H+K+PG2+PG3)	4.8	4.6	pf
PENTODE OUTPUT: PP TO (H+K+PG2+PG3)	1.6	0.9	pf
CATHODE TO HEATER: (K TO H)	6.0 ^B	6.0	pf
TRIODE GRID TO TRIODE PLATE: (TG TO TP)	1.5	1.5	рf
TRIODE INPUT: TG TO (H+K)	2.4	2.0	pf
TRIODE OUTPUT: TP TO (H+K)	1.0	0.5	pf
PENTODE GRID 1 TO TRIODE PLATE: (PG1 TO TP) MAX.	0.04	0.05	pf
PENTODE PLATE TO TRIODE PLATE: (PP TO TP) MAX.	0.008	0.05	ρf

CONTINUED ON FOLLOWING PAGE

AEXTERNAL SHIELD 315 CONNECTED TO PIN 3.

BEXTERNAL SHIELD 315 CONNECTED TO PIN 6.

--- TUNG-SOL ---

CONTINUED FROM PRECEDING PAGE

HEATER CHARACTERISTICS AND RATINGS

DESIGN MAXIMUM VALUES - SEE EIA STANDARD RS-239

AVERAGE CHARACTERISTICS HEATER WARM-UP TIME ^C	4.7 VOLTS	600 11	MA. SECONDS
HEATER SUPPLY LIMITS:			
VOLTAGE OPERATION		4.7	VOL TS
CURRENT OPERATION		600±40	MA.
MAXIMUM HEATER CATHODE VOLTA	GE:		
HEATER NEGATIVE WITH RESPEC	T TO CATHODE		
TOTAL DC AND PEAK		200	VOLTS
HEATER POSITIVE WITH RESPECT	T TO CATHODE		
DC		100	VOLTS
TOTAL DC AND PEAK		200	VOLTS

MAXIMUM RATINGS

DESIGN MAXIMUM VALUES - SEE EIA STANDARD RS-239

PENTODE PLATE VOLTAGE	275	VOLTS
TRIODE PLATE VOLTAGE	275	VOLTS
GRID 2 SUPPLY VOLTAGE	275	VOLTS
GRID 2 VOLTAGE	SEE J5-C4-2	
PENTODE PLATE DISSIPATION	2.3	WATTS
GRID 2 DISSIPATION	0.45	WATTS
POSITIVE DC GRID 1 VOLTAGE	0	VOL.TS
POSITIVE DC TRIODE GRID VOLTAGE	0 .	VOLTS
TRIODE PLATE DISSIPATION	1.7	WATTS

TYPICAL OPERATING CHARACTERISTICS

CLASS A1 AMPLIFIER

	TRIODE	PENTODE	
PLATE VOLTAGE	125	125	VOLTS
GRID 3 VOLTAGE	CONNECTED	TO PIN 3 AT SOCK	£Τ
GRID 2 VOLTAGE		125	VOLTS
GRID 1 VOLTAGE	-1.0	-1.0	VOLTS
TRANSCONDUCTANCE	6,500	5,500	μ MHOS
PLATE CURRENT	12.0	9.0	MA.
GRID 2 CURRENT		2.2	MA.
PLATE RESISTANCE (APPROX.)	6,000	300,000	OHMS
AMPLIFICATION FACTOR	40	****	
GRID 1 VOLTAGE (APPROX.) FOR 1b=20µA	-7	-6.5	VOLTS
ZERO BIAS TRANSCONDUCTANCE			
(WITH Eb = 100 V; Ec2 = 70 V)		5,700	μ MHOS

HEATER WARM-UP TIME IS DEFINED AS THE TIME REQUIRED FOR THE VOLTAGE ACROSS THE HEATER TO REACH 80% OF ITS RATED VOLTAGE AFTER APPLYING 4 TIMES RATED HEATER VOLTAGE TO A CIRCUIT CONSISTING OF THE TUBE HEATER IN SEREIS WITH A RESISTANCE OF VALUE 3 TIMES THE NOMINAL HEATER OPERATING RESISTANCE.

