

COATED UNIPOTENTIAL CATHODE


HEATER

6.3±0.3 VOLTS

0.3 AMP.

AC OR DC

ANY MOUNTING POSITION



BOTTOM VIEW BASING DIAGRAM JEDEC BDG

8DG

THE 6111 IS A SUBMINIATURE MEDIUM-MU TWIN TRIODE DESIGNED FOR USE IN GENERAL-PURPOSE AMPLIFIER APPLICATIONS. EACH SECTION HAS AN INDIVIDUAL CATHODE AND IS ELECTRICALLY INDEPENDENT. THE TUBE MAY ALSO BE USED AS A COMBINED OSCILLATOR AND MIXER IN HIGH-FREQUENCY CIRCUITS.

DIRECT INTERELECTRODE CAPACITANCES

	WITH A SHIELD	WITHOUT SHIELD		
GRID TO PLATE, EACH SECTION INPUT, EACH SECTION OUTPUT, SECTION 1 OUTPUT, SECTION 2 GRID TO GRID, MAX. PLATE TO PLATE, MAX.	1.4 2.1 1.3 1.4 0.010	1.5 1.9 0.28 0.32 0.011	pf pf pf pf pf	
	0.3	0.5	pf	

 $^{
m A}_{
m with}$ external shield of 0.405" inside diameter connected to cathode of section under test.

RATINGS

ABSOLUTE MAXIMUM VALUES

EACH SECTION

MAXIMUM PLATE VOLTAGE		
MAXIMUM NEGATIVE DC GRID VOLTAGE	165	VOLTS
MAXIMUM PLATE DISSIPATION	55	VOLTS
	0.95	WATTS
MAXIMUM DC PLATE CURRENT	22	MA.
MAXIMUM DC GRID CURRENT	5.5	
MAXIMUM HEATER-CATHODE VOLTAGE:	5.5	MA.
HEATER POSITIVE WITH RESPECT TO CATHODE		
HEATER NEGATIVE WITH RESPECT TO CATHODE	200	VOLTS
MAYIMIN COID CIDCUIT PERIODE	200	VOLTS
MAXIMUM GRID CIRCUIT RESISTANCE	1.1	MEGOHMS
MAXIMUM BULB TEMPERATURE AT HOTTEST POINT	220	C

CONTINUED ON FOLLOWING PAGE

TUME-SOL -

CONTINUED FROM PRECEDING PAGE

TYPICAL OPERATING CONDITIONS AND CHARACTERISTICS

CLASS A1 AMPLIFIER - EACH SECTION

PLATE VOLTAGE	100	VOL TS
CATHODE-BIAS RESISTOR	220	OHMS
AMPLIFICATION FACTOR	20	
PLATE RESISTANCE, APPROX.	4000	OHMS
TRANSCONDUCTANCE	5000	μMHOS
PLATE CURRENT	8.5	MA.
GRID VOLTAGE, APPROX. Ib = 10 μAMPERES	-9.0	VOLTS

CLASS A RESISTANCE- COUPLED AMPLIFIER

EACH SECTION

LOW IMPEDANCE DRIVE (APPROXIMATELY 200 OHMS)											
R _L R _{gf}		Ebb= 90 Volts			Ebb = 150 Volts			ЕЬЬ:	Ebb = 225 Volts		
_	. .	Rk	Е,	Gain	Rk	E o	Gain	R _k	Е,	Gain	
0.10	0.10	2400	8.4	13	2100	16	14	1900	25	15	
0.10	0.24	3100	12	14	2800	22	15	2600	34	16	
0.24	0.24	6200	10	14	5600	19	15	5200	30	16	
0.24	0.51	7800	13	14	7200	25	15	7000	38	15	
0.51	0.51	14000	11	13	13000	21	14	12000	32	15	
0.51	1.0	19000	14	13	17000	26	14	16000	40	15	
HIGH IMPEDANCE DRIVE (APPROXIMATELY 100K OHMS)											
R	R R Ebb = 90 Voits Ebb = 150 Voits				Ebb = 225 Volts						
-	gf	R _k	E.	Gain	R _k	Е,	Gain	R _k	€.	Gain	
0.10	0.10	3200	11	13	2500	21	14	2100	32	15	
0.10	0.24	4200	15	14	3400	28	15	3000	43	15	
0.24	0.24	8400	13	13	6800	24	14	6000	36	15	
0.24	0.51	10000	16	13	8700	29	15	7800	45	15	
0.51	0.51	17000	13	13	15000	25	14	13000	38	15	
0.51	1.0	21000	17	13	19000	30	14	17000	47	15	


NOTES:

- 1. E IS MAXIMUM RMS VOLTAGE OUTPUT FOR APPROXIMATELY FIVE PERCENT TOTAL HARMONIC DISTORTION.
- 2. GAIN IS MEASURED FOR AN OUTPUT VOLTAGE OF TWO VOLTS RMS.
- 3. R_k is in ohms; R_l and R_{gf} are in megohms.
- 4. COUPLING CAPACITORS (C) SHOULD BE SELECTED TO GIVE DESIRED FREQUENCY RESPONSE, \mathbf{R}_k SHOULD BE ADEQUATELY BY-PASSED.

HEATER CURRENT: Ef = 6.3 V

TUME-SOL

CONTINUED FROM PRECEDING PAGE



CHARACTERISTICS LIMITS

INITIAL

MIN

280

320

	500 HR.	276	328	MA.
PLATE CURRENT, EACH SECTION				
Ef =6.3 V., Eb =100 V., Rk =220 OHMS				
(BY PASSED)	INITIAL	6.0	11	MA.
PLATE CURRENT DIFFERENCE BETWEEN				
SECTIONS:				
DIFFERENCE BETWEEN PLATE CURRENTS F	OR			
EACH SECTION AT Ef =6.3 V., Eb =100 V.,				
Rk =220 OHMS (BY - PASSED)	INITIAL		2.0	MA.
TRANSCONDUCTANCE (1), EACH SECTION				
Ef =6.3 V., Eb =100 V., Rk =220 OHMS				
(BY-PASSED)	INITIAL	4100	5900	μMHOS
TRANSCONDUCTANCE CHANGE WITH				• • • • • • • • • • • • • • • • • • • •
HEATER VOLTAGE, EACH SECTION:				
DIFFERENCE BETWEEN TRANSCON-				
DUCTANCE (1) AND TRANSCONDUCTANCE				
AT Ef =5.7 VOLTS (OTHER CONDITIONS				
THE SAME) EXPRESSED AS A PERCENTAGE				
OF TRANSCONDUCTANCE (1)	INITIAL		15	PERCENT
	500 HR.		15	PERCENT
TRANSCONDUCTANCE CHANGE WITH				
OPERATION, EACH SECTION				
DIFFERENCE BETWEEN TRANSCON-				
DUCTANCE (1) INITIALLY AND AFTER				
OPERATION EXPRESSED AS A PERCENTAGE				
OF INITIAL VALUE	500 HR.		20	PERCENT
AVERAGE TRANSCONDUCTANCE CHANGE				
WITH OPERATION, EACH SECTION:				
AVERAGE OF VALUES FOR "TRANSCON-				
DUCTANCE CHANGE WITH OPERATION"	500 HR		15	PERCENT
AMPLIFICATION FACTOR, EACH SECTION:				
Ef =6.3 V., Eb = 100 V., Rk = 220 OHMS				
(BY-PASSED)	INITIAL	17	23	
PLATE CURRENT CUTOFF, EACH SECTION:				
Ef = 6.3 V., Eb = 100 V., Ec =-9.0 V.	INITIAL		100	μAMPS.
INTERELECTRODE CAPACITANCES:				μ Ο.
GRID TO PLATE (G TO P) EACH SECTION	INITIAL	1.2	1.8	μμt
INPUT (G TO K+H) , EACH SECTION	INITIAL	1.4	2.4	μμf
OUTPUT (P TO K+H), SECTION 1	INITIAL	0.20	0.36	μμt
OUTPUT (P TO K+H), SECTION 2	INITIAL	0.22	0.42	μμt
GRID TO GRID (G TOG)	INITIAL		0.011	μμ f
PLATE TOPLATE (P TO P)	INITIAL		0.50	μμ f
			, 0.00	
MEASURED WITHOUT EXTERNAL SHIELD.				

--- TUNG-SOL ---

CONTINUED FROM PRECEDING PAGE

CHARACTERISTICS LIMITS - cont'd.

NEGATIVE GRID CURRENT, EACH SECTION Ef = 6.3 V., Eb = 100 V., Rk = 220 OHMS				
(BY- PASSED) Rg = 1.0 MEG.	INITIAL		0.3	μAMPS.
HEATER-CATHODE LEAKAGE CURRENT: Ef = 6.3 V., Ehk = 100 V.,	500 HR.		0.9	μAMPS.
HEATER POSITIVE WITH RESPECT				
TO CATHODE	INITIAL		5.0	μAMPS.
	500 HR.		10	μAMPS.
HEATER NEGATIVE WITH RESPECT				
TO CATHODE	INITIAL		5.0	μΑΜΡS.
	500 HR.		10	μΑΜΡS.
INTERELECTRODE LEAKAGE RESISTANCE: Ef = 6.3 V., POLARITY OF APPLIED DC INTERELECTRODE VOLTAGE IS SUCH THAT NO CATHODE EMISSION RESULTS.				
GRID (EACH SECTION) TO ALL AT 100V.DC	INITIAL	100		MEGOHMS
01115 (=11011 025 17011) 10 1122 111 1001.50	500 HR.	50		MEGOHMS
PLATE (EACH SECTION) TO ALL AT 300V.DO		100		MEGOHMS
TEXTE TEXAN SECTION TO REE AT SOUR	500 HR.	50		MEGOHMS
VIBRATIONAL NOISE OUTPUT VOLTAGE, RMS: Ef = 6.3 V., Ebb = 100 V., Rk = 220 OHMS (BY-PASSED) R ₁ = 10,000 OHMS, VIBRATIONAL		33		WEGOTINE
ACCELERATION = 15 G AT 40 cps. GRID EMISSION CURRENT, EACH SECTION: Ef = 7.5 V., Eb ≃100 V., Ecc =−9.0 V.,	INITIAL		50	MV.
Rg = 1.0 MEG. PULSE CAT HODE CURRENT: Ef =6.0 V., PULSE OF 25 JSECONDS DURATION 200- CYCLE REPETITION RATE, AND 50 VOLTHING THE STAPPLIED TO PLATE AND GRIED TIED TOGETHER. PULSE CATHODE CURRENT IS MEASURED FOR EACH SECTION WITH OP-	Γ)		0.5	μAMP S.
POSITE SECTION FLOATING	INITIAL	300		MA.

SPECIAL TESTS AND RATINGS

STABILITY LIFE TEST

STATISTICAL SAMPLE OPERATED FOR ONE HOUR TO EVALUATE AND CONTROL INITIAL VARIATIONS IN TRANSCONDUCTANCE.

SURVIVAL RATE LIFE TEST

STATISTICAL SAMPLE OPERATED FOR ONE HUNDRED HOURS TO EVALUATE AND CONTROL EARLY-LIFE ELECTRICAL AND MECHANICAL IN-OPERATIVES.

HEATER-CYCLING LIFE TEST

STATISTICAL SAMPLE OPERATED FOR 2000 CYCLES TO EVALUATE AND CONTROL HEATER-CATHODE DEFECTS. CONDITIONS OF TEST INCLUDE EF=7.0 VOLTS CYCLED FOR ONE MINUTE ON AND FOUR MINUTES OFF, Eb=Ec=0 VOLTS, AND Ebk=140 VOLTS RMS.

SHOCK RATING--450 G

STATISTICAL SAMPLE SUBJECTED TO FIVE IMPACT ACCELERATIONS OF 450 G IN EACH OF FOUR DIF-FERENT POSITIONS. THE ACCELERATING FORCES ARE APPLIED BY THE NAYY-TYPE, HIGH IMPACT (FLYWEIGHT) SHOCK MACHINE FOR ELECTRONIC DEVICES OR ITS EQUIVALENT.

CONTINUED ON FOLLOWING PAGE

CONTINUED FROM PRECEDING PAGE

SPECIAL TESTS AND RATINGS - cont'd.

FATIGUE RATING-2.5 G

STATISTICAL SAMPLE SUBJECTED TO VIBRATIONAL ACCELERATION OF 2,5 G FOR 32 HOURS IN EACH OF THREE DIFFERENT POSITIONS. THE SINUSOIDAL VIBRATION IS APPLIED AT A FIXED FREQUENCY BETWEEN 25 AND 60 CYCLES PER SECOND.

ALTITUDE RATING -- 60,000 FEET

STATISTICAL SAMPLE SUBJECTED TO PRESSURE OF 55 MILLIMETERS OF MERCURY TO EVALUATE AND CONTROL ARCING AND CORONA.

NOTE:

THE CONDITIONS FOR SOME OF THE INDICATED TESTS HAVE DELIBERATELY BEEN SELECTED TO AGGRAVATE TUBE FAILURES FOR TEST AND EVALUATION PURPOSES. IN NO SENSE SHOULD THESE CONDITIONS BE INTERPRETED AS SUITABLE CIRCUIT OPERATING CONDITIONS.

IN THE DESIGN OF MILITARY EQUIPMENT EMPLOYING THIS TUBE, REFERENCE SHOULD BE MADE TO THE APPROPRIATE MIL-E-1 SPECIFICATION.

