
# - JOS-BKUT

#### DIODE PENTODE

MINIATURE TYPE




9 FIN BASE E9-1 OUTLINE DRAWING JEDEC 6-2 COATED UNIPOTENTIAL CATHODE

HEATER

6.3±10% VOLTS 450 MA.

AC OR BC

ANY MOUNTING POSITION



BOTTOM VIEW
BASING DIAGRAM
JEDEC 2CY

THE 6AMBA IS A DIODE PENTODE EXPECIALLY DESIGNED FOR USE AS A VIDEO DETECTOR AND IF AMPLIFIED IN TELEVISION RECEIVERS. IN ADDITION, THERMAL CHARACTERISTICS OF THE HEATER ARE CONTROLLED SUCH THAT HEATER VOLTAGE SURGES DURING THE WARM-UP CYCLE ARE MINIMIZED PROVIDED IT IS USED WITH OTHER TYPES WHICH ARE SIMILARLY CONTROLLED.

### DIRECT INTERELECTRODE CAPACITANCES

	SHIELD <sup>A</sup>	WITHOUT SHIELD	
PENTODE  GRID #1 TO PLATE (MAX.)	0.015	0.015	рf
INPUT	6.0	6.5	рf
OUTPUT	3.4	2.6	рf
DIODE			
INPUT: P TO (H+K)	2.3	1.8	рf
CATHODE TO (H+P)	3.0	3.0	рf
COUPLING (DIODE PLATE TO PENTODE PLATE)	0.035	0.10	рf
COUPLING (DIODE PLATE TO GRID #1)	0.005	0.006	рf
COUPLING (DIODE CATHODE TO PENTODE PLATE)	0.15	0.15	рf

ASHIELD #315 CONNECTED TO GROUND.

CONTINUED ON FOLLOWING PAGE

## TUNG-SOL -

CONTINUED FROM PRECEDING PAGE

# RATINGS INTERPRETED ACCORDING TO DESIGN MAXIMUM SYSTEM

MAXIMUM HEATER-CATHODE VOLTAGE:		
HEATER NEGATIVE WITH RESPECT TO CATHODE		
TOTAL DC AND PEAK	200	VOLTS
HEATER POSITIVE WITH RESPECT TO CATHODE		
DC	100	VOLTS
TOTAL DC AND PEAK	200	VOLTS
MAXIMUM PLATE VOLTAGE	330	VOLTS
MAXIMUM PLATE DISSIPATION	3.2	WATTS
MAXIMUM GRID #2 VOLTAGE	SEE RATING	CHART
MAXIMUM GRID #2 SUPPLY VOLTAGE	330	VOLTS
MAXIMUM GRID #2 DISSIPATION	0.55	WATTS
MAXIMUM POSITIVE GRID #1 VOLTAGE	0	VOLTS
MAXIMUM GRID #3 VOLTAGE	0	VOLTS
MAXIMUM GRID #1 CIRCUIT RESISTANCE:		
CATHODE BIAS	1.0	MEGOHM
FIXED BIAS	0.25	MEGOHM
MAXIMUM DIODE CURRENT FOR CONTINUOUS OPERATION	5.0	MA.
HEATER WARM-UP TIME (APPROX.)*	11.0	SECUNDS

<sup>\*</sup>HEATER WARM-UP TIME IS DEFINED AS THE TIME REQUIRED FOR THE VOLTAGE ACROSS THE HEATER TO REACH 80\$ OF ITS RATED VOLTAGE AFTER APPLYING 4 TIMES RATED HEATER VOLTAGE TO A CIRCUIT CONSISTING OF THE TUBE HEATER IN SERIES WITH A RESISTANCE OF VALUE 3 TIMES THE NOMINAL HEATER OPERATING RESISTANCE.

#### TYPICAL OPERATING CONDITIONS AND CHARACTERISTICS

PLATE VOLTAGE	125	VOLTS
GRID #2 VOLTAGE	125	VOL TS
GRID #3 VOLTAGE	0	VOLTS
CATHODE RESISTOR	56	OHMS
PLATE CURRENT	12.5	MA.
GRID #2 CURRENT	3.2	MA.
TRANSCONDUCTANCE	7 800	μMH0S
PLATE RESISTANCE (APPROX.)	0.3	ME GOHM
GRID #1 VOLTAGE FOR $I_b = 20 \mu A$ . (APPROX.)	-6	VOLTS
PLATE CURRENT AT Ect =-3V., Rk =0	2.0	MA.
DIODE PLATE VOLTAGE FOR		
DIODE CURRENT = 50 MA.	10	VOLTS

DESIGN-MAXIMUM RATINGS ARE LIMITING VALUES OF OPERATING AND ENVIRONMENTAL CONDITIONS APPLICABLE TO A BOGEY ELECTRON DEVICE OF A SPECIFIED TYPE AS DEFINED BY ITS PUBLISHED DATA, AND SHOULD NOT BE EXCEEDED UNDER THE WORST PROBABLE CONDITIONS. THE DEVICE MANUFACTURER CHOOSES THESE VALUES TO PROVIDE ACCEPTABLE SERVICEABILITY OF THE DEVICE, TAKING RESPONSIBILITY FOR THE EFFECTS OF CHANGES IN OPERATING COMDITIONS DUE TO VARIATIONS IN DEVICE CHARACTERISTICS. THE EQUIPMENT MANUFACTURER SHOULD BESION SO THAT INITIALLY AND THROUGHOUT LIFE NO DESIGN-MAXIMUM VALUE FOR THE INTEMDED SERVICE IS EXCEEDED WITH A BOGEY DEVICE UNDER THE APRIL VARIATION, EQUIPMENT COMPONENT VARIATION, EQUIPMENT COMPONENT VARIATION, EQUIPMENT COMPONENT VARIATION, EQUIPMENT CONTROL ADJUSTMENT, LOAD VARIATION, SIGNAL VARIATION, AND ENVIRONMENTAL CONDITIONS.

