
TUNG-SOL -





BOTTOM VIEW SHORT MEDIUM SHELL 7 PIN OCTAL 6AN

GLASS BULB

THE 6CU6 IS A BEAM-POWER TUBE INTENDED FOR USE AS A HORIZONTAL DEFLECTION AMPLIFIER IN TELEVISION RECEIVERS. IT IS DESIGNED TO PROVIDE LONGER LIFE AT HIGH-LINE CONDITIONS AND INCREASED RUGGEDNESS TO WITHSTAND MOMENTARY OVERLOADS.

DIRECT INTERELECTRODE CAPACITANCES

GRID #1 TO PLA	ATE: G ₁ TO P	0.6 ←	– <i>ա</i> աք
INPUT: G1 TO	(H+K+G2+BP)	15 ←	- μμ f
OUTPUT: P TO	(H+K+G ₂ +BP)	7 🕶	_ μμ f

RATINGS A INTERPRETED ACCORDING TO RETMA STANDARD M8-210 HORIZONTAL DEFLECTION AMPLIFIER B

HEATER VOLTAGE	6.3	VOLTS
MAXIMUM HEATER-CATHODE VOLTAGE:		
HEATER NEGATIVE WITH RESPECT TO CATHODE TOTAL DC AND PEAK	200	VOLTS
HEATER POSITIVE WITH RESPECT TO CATHODE		
DC TOTAL DC AND PEAK	100	VOLTS VOLTS
	200	
MAXIMUM DC PLATE SUPPLY VOLTAGE (BOOST+POWER SUPPLY)	600 ←	VOLTS
MAXIMUM PEAK POSITIVE PLATE VOLTAGE (ABSOLUTE MAXIMUM)	6 000	VOLTS
MAXIMUM PEAK NEGATIVE PLATE VOLTAGE	1 250	VOLTS
MAXIMUM PLATE DISSIPATION ^C	11	WATTS
MAXIMUM PEAK NEGATIVE GRID #1 VOLTAGE	300	VOLTS
MAXIMUM DC GRID #2 VOLTAGE	200 🕶	VOL TS
MAXIMUM GRID #2 DISSIPATION	2.5	WATTS
MAXIMUM AVERAGE CATHODE CURRENT	110	MA -
MAXIMUM PEAK CATHODE CURRENT	400	MA.
MAXIMUM GRID #1 CIRCUIT RESISTANCE	0.47	ME GOHM
MAXIMUM BULB TEMPERATURE (AT HOTTEST POINT)	220	°С

ADESIGN CENTER VALUES EXCEPT WHERE ABSOLUTE MAXIMUM IS STATED.

CONTINUED ON FOLLOWING PAGE.

B FOR OPERATION IN A 525-LINE, 30-FRAME SYSTEM AS DESCRIBED IN "STANDARDS OF GOOD ENGINEERING PRACTICE FOR TELEVISION BROADCASTING STATIONS; FEDERAL COMMUNICATIONS COMMISSION". THE DUTY CYCLE OF THE VOLTAGE PULSE MUST NOT EXCEED 15% (10 MICROSECONDS) OF A SCANNING CYCLE.

 $^{^{\}rm C}$ in stages operating with grid-leak bias, an adequate cathode-bias resistor or other suitable means is required to protect the tube in the absence of excitation.


-- TUNG-SOL -

CONTINUED FROM PRECEDING PAGE

TYPICAL OPERATING CONDITIONS AND CHARACTERISTICS -

PENTODE OPERATION: WITH $E_b = 250 \text{V}$, $E_{c2} = 150 \text{V}$. AND $E_{c1} = -22.5 \text{V}$.			
PLATE CURRENT		57	MA.
GRID #2 CURRENT		2.1	MA.
TRANSCONDUCTANCE	5	900	µMH0S
PLATE RESISTANCE (APPROX.)	14	500	OHMS
ZERO BIAS: WITH Eb = 60V. AND Ec2 = 150V. (INSTANTANEOUS VALUES)			
PLATE CURRENT		260	MA -
GRID #2 CURRENT		26	MA.
CUT-OFF: FOR I_b = 1 MA., WITH E_b = 250V. AND E_{c2} = 150V.			
GRID #1 VOLTAGE (APPROX.)		-43	VOLTS
TRIODE 4: WITH Eb = Ec2 = 150V. AND Ec1 =-22.5V.		4.3	

SINILAR TIPE REPERENCE. Except for heater operation the 6006 is identical to the 12006 and 25006. It is a rugged replacement for the 68066F.



PRINTED 12 V. D. A.