
TUMB-SOL

PENTODE

MINIATURE TYPE



COATED UNIPOTENTIAL CATHODE

HEATER

6.3 VOLTS 0.3 AMP.

AC OR DC

ANY MOUNTING POSITION



BOTTOM VIEW
MINIATURE BUTTON
7 PIN BASE

7 F W

THE 6GN6 IS A REMOTE-CUTOFF PENTODE IN THE 7 PIN MINIATURE CONSTRUCTION. IT IS DESIGNED PRIMARILY FOR USE AS A HIGH GAIN R.F. OR I.F. AMPLIFIER AND A DEMODULATOR DIODE BOTH ON A COMMON CATHODE. EXCEPT FOR HEATER CHARACTERISTICS AND HEATER WARM-UP TIME, THE 6GN6 IS IDENTICAL TO THE 12GN6.

DIRECT INTERELECTRODE CAPACITANCES

	WITH A SHIELD	WITHOUT SHIELD	
GRID #1 TO PLATE (MAX.)	.0035	.0035	µµ f
INPUT OUTPUT	5.5 5.5	5.5 5.0	ии f ии f
COUPLING DIODE PLATE TO GRID (MAX.)	.05	.05	μμ f

Awith external shield #316 connected to Pin 2.

RATINGS

INTERPRETED ACCORDING TO DESIGN CENTER SYSTEM

HEATER VOLTAGE	6.3	VOLTS
MAXIMUM PLATE VOLTAGE	300	VOLTS
MAXIMUM SCREEN-SUPPLY VOLTAGE	300	VOLTS
MAXIMUM POSITIVE GRID #1 VOLTAGE	0	VOLTS
MAXIMUM NEGATIVE GRID #1 VOLTAGE	50	VOLTS
MAXIMUM PLATE DISSIPATION	3.0	WATTS
MAXIAUM SCREEN DISSIPATION	0.6	WATTS
MA) IMUM DIODE CURRENT (CONTINUOUS OPERATION)	1.0	MA.
MAZIMUM HEATER-CATHODE VOLTAGE:		
HEATER POSITIVE WITH RESPECT TO CATHODE		
DC COMPONENT	100	V OL T S
TOTAL DC PLUS PEAK	200	VOLTS
HEATER NEGATIVE WITH RESPECT TO CATHODE		
TOTAL DC PLUS PEAK	200	VOLTS
HEATER WARM-UP TIME* (APPROX.)	11.0	SECONDS

^{*}HEATER WARM-UP TIME IS DEFINED AS THE TIME REQUIRED FOR THE VOLTAGE ACROSS THE HEATER TO REACH 80% OF ITS RATED VOLTAGE AFTER APPLYING 4 TIMES RATED HEATER VOLTAGE TO A CIRCUIT CONSISTING OF THE TUBE MEATER IN SERIES WITH A RESISTANCE OF VALUE 3 TIMES THE NOMINAL HEATER OPERATING RESISTANCE.

CONTINUED ON FOLLOWING PAGE

----- TUNG-SOL ------

CONTINUED FROM PRECEDING PAGE

TYPICAL OPERATING CONDITIONS AND CHARACTERISTICS

CLASS A1 AMPLIFIER

HEATER VOLTAGE HEATER CURRENT		.3 .3	VOLTS AMP.
PLATE VOLTAGE	100	250	VOLTS
SUPPRESSOR, CONNECTED TO CATHODE AT SOCKET			
SCREEN VOLTAGE	100	100	VOLTS
CATHODE-BIAS RESISTOR	68	.68	OHMS
PLATE RESISTANCE (APPROX.)	0.25	1.0	MEGOHMS
TRANSCONDUCTANCE	4300	4400	μ м нοs
PLATE CURRENT	10.8	11	MA.
SCREEN CURRENT	4.4	4.2	MA.
GRID #1 VOLTAGE (APPROX.)			
$G_m = 40 \mu MHOS$	-20	-20	VOLTS
AVERAGE DIODE CURRENT AT 10V D.C.	1.5	1.5	MA.