## DOUBLE-RESONATOR KLYSTRON



Frequency: 'X' band, mechanically tunable. Power outbut: 180W min at 10Gc/s.

Construction: Double resonator, water-cooled.

This data should be read in conjunction with GENERAL OPERATIONAL RECOMMENDATIONS – MICROWAVE DEVICES which precede this section of the handbook.

#### FREQUENCY RANGE

8.6 to 10 Gc/s

Mechanical tuning is effected by two calibrated controls.

#### CATHODE

Indirectly heated

 $V_{\rm h}$  6.3 V  $I_{\rm h}$  800 mA

Heating time. The heater voltage should be applied at least 3 minutes before the application of h.t. voltage.

#### MOUNTING POSITION

Any

Two 2BA holes are provided in the resonator block to facilitate mounting and to prevent the whole weight of the valve being placed on the waveguide flange.

### COOLING

Maximum temperature of outlet water

40 °C

Two water jackets are used, one surrounding the two resonators, the other the collector. When the two jackets are connected in series to a common water supply the inlet must be on the collector side. Rate of flow should be >1/2 gal/min and <1 gal/min.

### LIMITING VALUES (absolute ratings)

Maximum collector and resonators voltage	10	k٧
Maximum collector and resonators dissipation	2.0	kW
Maximum collector current	250	mΑ
Maximum negative grid voltage	250	٧
Maximum positive grid voltage	20	٧
Maximum standing wave ratio	1.5	



#### TYPICAL OPERATION

IIICAL OI LINAIION				
Principal Mode (Mode A)				
Frequency	8.6	9.3	10	Gc/s
Resonators/collector voltage	5.5	7.3	9.2	k٧
Grid Voltage	-50	<b>–50</b>	50	٧
Collector current	96	145	200	mΑ
Power input	0.53	1.1	1.8	kW
Resonators/collector dissipation	0.488	0.958	1.63	kW
Average power output	40	100	210	W
Power output	>30	>80	>180	W
Mode B				
Frequency			9.3	Gc/s
Resonators/collector voltage			4.3	k٧
Grid voltage			-50	٧
Collector current			65	mΑ
Power input			280	W
Resonators/collector dissipation			262	W
Power output			>18	W

#### **OPERATING NOTES**

- To ensure good frequency and amplitude stability the resonators and collector voltages should be taken from a stabilised supply; the voltage variation should not exceed ±10V (i.e. approximately 0.1%) if a frequency stability of 1:100.000 is to be maintained.
- For the safety of personnel it is advisable to operate with the positive pole of the h.t. supply earthed.
- 3. For mobile applications anti-vibration mounting is recommended, to avoid undesirable amplitude or phase modulation.
- 4. The tube must be shielded from strong external magnetic fields.
- 5. The number of mechanical tuning operations extending below about 9Gc/s or above 9.5Gc/s should be limited to 100, to avoid damage to the flexible diaphragm; between these frequencies there need be no limitations.

#### WEIGHT

Valve only	$ \begin{cases} 5 \text{ lb} & 3 \text{ oz} \\ 2.35 & \text{kg} \end{cases} $
Shipping weight	$ \left\{ \begin{array}{ll} 9 \text{ lb } 11 \text{ oz} \\ 4.4 & \text{kg} \end{array} \right. $
Dimensions of packing	$ \begin{cases} 197 & \times 203 & \times 248 & mm \\ 7.75 \times & 8.0 \times & 9.75 & in \end{cases} $



# DOUBLE-RESONATOR KLYSTRON

# **KB9-150W**

