

R = 31.5 ohms.

2. External conductive coating must be grounded.

quire that these values be about 5 volts more negative.

# engineering data service


#### CHARACTERISTICS


GENERAL DATA	
Focusing Method	
Horizontal	00 Degrees 04 te m
Faceplate	ss 74 Percent
ELECTRICAL DATA	
Heater Voltage	11 Seconds 5 μμf 6 μμf 10 μμf Max.
Ion Trap Magnet External, Single Field Typ	00 μμf Min.
MECHANICAL DATA Minimum Useful Screen Dimensions	
(Maximum Assured) $19\frac{1}{16}$ x $15\frac{1}{16}$ Minimum Useful Screen Area262 SoBulb Contact (Recessed Small Cavity Cap)J1-2Base (Small Shell Duodecal 5-Pin)B5-5Basing121	q. Inches 21 57
RATINGS	
MAXIMUM RATINGS (Absolute Maximum Values)	
Anode Voltage	0 Volts dc
Negative Peak Value	0 Volts 0 Volts dc
Heater Negative with Respect to Cathode During Warm-up Period not to Exceed 15 Seconds 45 After Equipment Warm-up Period	0 Volts
TYPICAL OPERATING CONDITIONS	
Anode Voltage	0 Volts dc 2 Volts dc % Ma dc 0 Ma dc
CIRCUIT VALUES	
Grid No. 1 Circuit Resistance	5 Megohms Max.
NOTES: (Continued on Page 2)	
1. Heater warm-up time is the time required for the voltage across the to increase to 5.0 volts in the JETEC test circuit, with $E=2$	

3. Visual extinction of focused raster. Extinction of stationary focused spot will re-

### QUICK REFERENCE DATA

Television Picture Tube
21" Direct Viewed
Rectangular Glass Type
Spherical Faceplate
Gray Filter Glass
Magnetic Deflection
Magnetic Focus
Single Field Ion Trap
External Conductive Coating
Aluminized Screen





## SYLVANIA ELECTRIC PRODUCTS INC.

TELEVISION PICTURE TUBE DIVISION

SENECA FALLS, NEW YORK

Prepared and Released By The
TECHNICAL PUBLICATIONS SECTION
EMPORIUM, PENNSYLVANIA
APRIL 1956


PAGE 1 OF 2

#### SYLVANIA

## **21BSP4**

PAGE 2

- 4. For JETEC focusing coil 109 or equivalent three inches from reference line, bias adjusted to 20 foot lamberts on a  $19\frac{1}{16}$  x  $15\frac{1}{16}$  inch picture area sharply focused at center of screen.
- 5. For JETEC Ion Trap Magnet No. 117 with pole pieces centered over Grid No. 2 on mount, and rotated for maximum brightness.
- 6. For typical PM ion trap magnet with field strength tolerance of  $\pm 3$  gausses.



#### **DIAGRAM NOTES:**

- 1. Reference line is determined by the plane C-C' of the reference line gauge (JETEC No. 116) when the gauge is resting on the glass cone.
- 2. Contact area for external conductive coating, 2" x 2", located 90 degrees counterclockwise from anode contact as viewed from base end of tube.
- 3. Anode contact aligns with vacant pin position No. 6 ±30 degrees.

#### **WARNING:**

X-ray radiation shielding may be necessary to protect against possible danger of personal injury from prolonged exposure at close range if this tube is operated at higher than the manufacturer's Maximum Rated Anode Voltage or 16,000 volts, whichever is less.