

### 2C39-B PLANAR TRIODE

2C39-B ET-T1054B Page 1 12-61



#### DESCRIPTION AND RATING=

#### FOR GROUNDED-GRID OSCILLATOR AND AMPLIFIER SERVICE

Metal and Ceramic High Transconductance Low Interelectrode Capacitances Shock Resistant

100 Watts Plate Dissipation

The 2C39-B is a metal-and-ceramic, high-mu triode designed for use as a grounded-grid oscillator or amplifier at frequencies as high as 2500 megacycles.

Features of the 2C39-B include planar electrode construction, high plate dissipation capability, excellent electrode isolation, low radio-frequency losses, high transconductance, and low interelectrode capacitances.

#### **GENERAL**

ELECTRICAL		MECHANICAL			
Cathode—Coated Unipotential Heater Characteristics and Ratings Heater Voltage, AC or DC* Heater Current at Ef = 6.3 volts	Amperes pf pf	Mounting Position—Any—Only Plate Flange to Be Used as a Socket Stop and Clamp Net Weight, approximate			
		Incoming Air Temperature 25C, Plate			

#### MAXIMUM RATINGS

Dissipation

#### **ABSOLUTE-MAXIMUM VALUES** RADIO-FREQUENCY POWER AMPLIFIER AND OSCILLATOR— **CLASS C TELEGRAPHY**

Key-Down Conditions per Tube Witho Modulation§	ut Amplitude
Heater Voltage*	Volts
DC Plate Voltage	Volts
Negative DC Grid Voltage	Volts
Peak Positive RF Grid Voltage 30	Volts
Peak Negative RF Grid Voltage400	Volts
DC Grid Current 50	Milliamperes
DC Cathode Current	Milliamperes
Plate Dissipation	Watts
Grid Dissipation 2.0	Watts
Envelope Temperature at Hottest	
Point *	С

#### RADIO-FREQUENCY POWER AMPLIFIER AND OSCILLATOR-**CLASS C TELEPHONY**

100 Watts......12.5 Cubic Feet

Per Minute

Carrier Conditions per Tube For Use With a Maximum Modulation Factor of 1.0

Heater Voltage* 4.5 to 6.3  DC Plate Voltage¶ 600  Negative DC Grid Voltage 150  Peak Positive RF Grid Voltage 400  DC Grid Current 50  DC Cathode Current 100  Plate Dissipation 70  Grid Dissipation 200	Volts Volts Volts Volts Milliamperes Milliamperes Watts
Grid Dissipation 2.0	Watts
Envelope Temperature at Hottest Point *	С



## **2C39-B** ET-T1054B Page 2 12-61

#### CHARACTERISTICS AND TYPICAL OPERATION

#### **AVERAGE CHARACTERISTICS**

Heater Voltage	Volts
Plate Voltage	Volts
Grid Voltage△	Volts
Amplification Factor	
Transconductance24800	Micromhos
Plate Current	Milliamperes

- \* The equipment designer should design the equipment so that heater voltage is centered at some value within the range of 4.5 to 6.3 volts. Heater voltage variations about the center value should be kept as small as practical and should not, in any case, exceed ±5%. The optimum center value of heater voltage depends on the cathode current and on other parameters of circuit design and operation. For specific recommendations, contact your General Electric tube sales representative.
- † Heater current of a bogey tube at Ef = 6.3 volts.

#### RADIO FREQUENCY OSCILLATOR—CLASS C

Frequency	2500	Megacycles
Heater Voltage	5.0	Volts
DC Plate Voltage900	900	Volts
DC Plate Current 90	90	Milliamperes
DC Grid Current30	27	Milliamperes
DC Grid Voltage40	-22	Volts
Useful Power Output	17	Watts

- † Measured in a special shielded socket.
- Modulation essentially negative may be used if the positive peak of the audio-frequency envelope does not exceed 115 percent of the carrier conditions.
- \*Where long life and reliable operation are important, lower envelope temperatures should be used.
- ¶ For modulation factors less than 1.0, a higher d-c plate voltage may be used if the sum of the peak positive audio voltage and the d-c plate voltage does not exceed 1200 volts. △Adjusted for Ib = 75 milliamperes.

#### INITIAL CHARACTERISTICS LIMITS

	Min.	Bogey	Max.	
Heater Current				
Ef = 6.3 volts	950	1030	1100	Milliamperes
Grid Voltage				
Ef = 6.3 volts, Eb = 600 volts, Ib = 75 ma	-1.3	-2.5	-3.5	Volts
Grid Voltage				
Ef = 6.3 volts, Eb = 600 volts, Ib = 1.0 ma	-7.0	-9.5	-15	Volts
Transconductance				
Ef = 6.3 volts, Eb = 600 volts, Ec adjusted for Ib = 75 ma	22000	24800	27500	Micromhos
Amplification Factor				
Ef = 6.3 volts, Eb = 600 volts, Ec adjusted for Ib = 75 ma	75	95	115	
Negative Grid Current				
Ef = 6.3 volts, Eb = 600 volts, Ec adjusted for Ib = 75 ma			3.0	Microamperes
Interelectrode Leakage Resistance				
Ef = 6.3 volts, Polarity of applied d-c interelectrode voltage is such that no				
cathode emission results				
Grid to Cathode at 500 volts d-c	50			Megohms
Interelectrode Capacitances				
Grid to Plate: (g to p)	1.89	2.01	2.13	Picofarads
Grid to Cathode: (g to k)	6.0	6.5	7.0	Picofarads
Plate to Cathode: (p to k)	0.018	0.023	0.029	Picofarads

Absolute-Maximum ratings are limiting values of operating and environmental conditions applicable to any electron tube of a specified type as defined by its published data and should not be exceeded under the worst probable conditions.

The tube manufacturer chooses these values to provide acceptable serviceability of the tube, making no allowance for equipment variations, environmental variations, and the effects of changes in operating conditions due to variations in the characteristics of the tube under consideration and of

all other electron devices in the equipment.

The equipment manufacturer should design so that initially and throughout life no absolute-maximum value for the intended service is exceeded with any tube under the worst probable operating conditions with respect to supply-voltage variation, equipment component variation, equipment control adjustment, load variation, signal variation, environmental conditions, and variations in the characteristics of the tube under consideration and of all other electron devices in the equipment.

The tubes and arrangements disclosed herein may be covered by patents of General Electric Company or others. Neither the disclosure of any information herein nor the sale of tubes by General Electric Company conveys any license under patent claims covering combinations of tubes with other devices or

elements. In the absence of an express written agreement to the contrary, General Electric Company assumes no liability for patent infringement arising out of any use of the tubes with other devices or elements by any purchaser of tubes or others.

#### SPECIAL PERFORMANCE TESTS

#### Min. Max.

Watts

#### Oscillator Power Output

Tubes are tested for power output as an oscillator under the following conditions:

Ef = 5.0 volts; F = 2500 MC, min.; Eb = 1000 volts; Ib = 90

#### Low Pressure Voltage Breakdown Test

Statistical sample tested for voltage breakdown at a pressure of 27 mm Hg. Tubes shall not give visual evidence of flashover when 1000 volts RMS, 60 cps, is applied between the plate and grid terminals.

#### **DEGRADATION RATE TESTS**


#### Shock

Statistical sample subjected to 5 input accelerations of approximately 400 G and 1.0 milliseconds duration in each of four positions. The accelerating forces are applied by the Navy-type, High Impact (flyweight) Shock Machine.

#### 500-Hour Life Test


Statistical sample operated for 500 hours as an oscillator to evaluate changes in power output with life.


#### PHYSICAL DIMENSIONS





#### NOTES:

- 1. Solder not to extend radially beyond grid RF terminal.
- 2. Total indicated runout of the grid-contact surface and the cathode-contact surface with respect to the anode shall not exceed 0.020''.
- 3. Total indicated runout of the cathode-contact surface with respect to the heater-contact surface shall not exceed 0.012".
- 4. Only this flange to be used as a socket stop and clamp.
- New pages 3 to 6 supersede old pages 3 and 4 dated 12-61.









# GENERAL ELECTRIC Owensboro, Kentucky