

Hoffman 6G15 Reverb Unit BOM

11/22/2024

Item	Component	Wattage	Notes
R1	1m	1/2 watt	
R2	10k	3 watt	
R3	100k	1/2 watt	
R4	1.5k	1/2 watt	
R5	250kl Pot		Dwell
R6	100k	1/2 watt	
R7	1.5k	1/2 watt	
R8	220k	1/2 watt	
R9	1k	5 watt	
R10	220k	1/2 watt	
R11	100k	1/2 watt	
R12	1.5k	1/2 watt	
R13	50kl Pot		Tone
R14	250kl Pot		Mix
R15	2.2m	1/2 watt	
R16	2.2m	1/2 watt	
R17	100k	1/2 watt	
R18	10k	3 watt	Power Supply
R19	100 ohm	1/2 watt	Heater center tap
R20	100 ohm	1/2 watt	Heater center tap
R99	180 ohm	1/2 watt	If using LED
Item	Component	Voltage	Notes
C1	22uf	50v	or 25uf/25v
C2	.01uf	400-630v	
C3	.0022uf	400-630v	
C4	22uf	50v	or 25uf/25v
C5	220uf	35v	
C6	.1uf	400-630v	
C7	.01uf	400-630v	
C8	250p	400-630v	
C9	.1uf	400-630v	
C10	.047uf	400-630v	
C11	47uf	500v	Filter Cap
C12	47uf	500v	Filter Cap
C13	47uf	500v	Filter Cap
Item	QTY	Component	Notes
T1	1	Mojo 779	Power Transformer
T2	1	Mojo 771	Output Transformer
T3	1	125C3A	Choke
Tank	1	9AB3C1B	Reverb Tank
Bag	1	Tank Bag	Reverb Tank Bag
Bridge	1	1000 volt - 3 amp	Bridge Rectifier
SW1	1	SPST Switch	Power On/Off
SW2	1	SPST Foot Switch	Reverb On/Off
J1	1	12A Switchcraft jack	Input Jack
J2	1	12A Switchcraft jack	Output Jack
J3	1	RCA jack	Reverb Send
J4	1	RCA jack	Reverb Return
J5	1	RCA jack	Reverb Foot Switch

Hoffman 6G15 Reverb Unit BOM

Tubes	1	12AT7	V1
Tubes	1	12AX7	V2
Tubes	1	6V6 or 6K6	V3
Socket	2	9 pin Tube Sockets with shield	V1,V2
Socket	1	8 pin Tube Socket	V3
Board	1	6G15 Turret Board	
Lugs	45	Turret lugs	
Standoffs	4	1/4" Nylon Standoffs	Circuit board mounting
Screws	4	# 8 x 5/8" Screws	Circuit board mounting
Nuts	4	#8 Keps nuts	Circuit board mounting
Knobs	3	Your choice of style	
Power cord	1	8, or 12 foot cord	
Power cord strain relief	1		
Power cord clamp	1		
Fuse Holder	1	Fender style or mashall Style	
Fuse	1	1 amp slo-blo	
Pilot	1	Pilot Lamp or LED	Use 180 ohm resistor for LED
Bulb	1	Pilot Lamp	If using Lamp assembly
Jewel	1	Pilot Lamp	If using Lamp assembly
Wire	8 ft	Mini Shielded cable	
Wire	8 ft	Bus wire	Used to lace the lugs
Wire	20 ft	20 Gauge hookup wire	Red, Black, Green, White
Wire	20 ft	18 Gauge hookup wire	Red, Black, Green, White
Heat Shrink	1 ft	Heat shrink tubing	.125 diameter
Chassis	1	Chassis	
Grommets	2	3/8 inch	

[Hoffman Amplifiers Tube amp Library Page](#)[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM

[illegible]

Hoffman 6G15 Reverb Unit BOM
